1300 883 452
sales@cableaway.com.au
www.cableaway.com.au


LINE8 POWER TRACK — MODULAR POWER SOCKET SYSTEMS


Line8 Power Sockets — Type I

BD-AUN1-CR

Also available as **BD-AUN1-OB** (Onyx Black) — see Ordering Information









Line8 Type I power sockets for all Line8 power tracks. Insert, twist and pull the ring to switch on – an orange indicator shows when the socket is live. Add sockets at any time as your needs grow, move them along the track, or take them between rooms fitted with Line8. Available individually or as a pack of 3, with a Chrome Ring or Onyx Black finish.

TECHNICAL SPECIFICATIONS

Socket Type	**Australian Type I (AS/NZS 3112)**
Compatibility	**All Line8 power tracks – surface and recessed, all finishes**
Ring Finish	**Chrome Ring / Onyx Black**
Pack Options	**Single socket / Pack of 3**
Capacity	**Up to 14 sockets per metre of track**
Switching	**Push-pull ring switch with orange on indicator**
Warranty	**5 years**

ORDERING INFORMATION

Pack of 3 – Chrome Ring	**BD-AUN1-CR**
Pack of 3 – Onyx Black	**BD-AUN1-OB**
Single – Chrome Ring	**Single socket – Chrome Ring**
Single – Onyx Black	**Single socket – Onyx Black**

AT A GLANCE

Type I SOCKET	STANDARD **AS/NZS 3112**	RING FINISH **Chrome / Onyx**
	PACK **Single / 3**	WARRANTY **5 Years**

KEY FEATURES

- Fits anywhere along any Line8 power track – no tools required
- Lock-and-key contacts – only a genuine Line8 socket can engage the track
- Track stays unpowered until the socket is seated and switched on
- Typical installations use 6–9 sockets per track
- Sockets move with you – reuse on future Line8 installations

TYPICAL APPLICATIONS

✓ Kitchens, pantries & island benches	✓ Joinery, desks & vanities
✓ Offices & boardrooms	✓ Hotels & hospitality lounges
✓ Aged care & healthcare	✓ Schools & universities
✓ Retail & laboratories	✓ Commercial fit-outs

COMPLIANCE & CERTIFICATION

Standards	**AS/NZS 3100 / AS/NZS 3112**
Approval	**RCM marked (AU & NZ)**
Quality & Test	**ISO 9001, IEC 61534**
Installation	**Licensed electrician only**